# Denver® Square Wireless Configurable Keypad



## Denver® Square Wireless Configurable Keypad, C4-SKC-N

The Denver® Wireless Configurable Keypad is an elegant and customizable user interface that unlocks the power of one touch automation. The keypad can be configured with two to seven buttons using five different button sizes for a total of 38 possible configurations. There's no need to worry about how many buttons will be needed on a specific keypad prior to (or even after) installation.

• Wireless communication and standard wiring provide easy installation in new construction and retrofit environments.

- · Elegant, sophisticated design makes a beautiful addition to any home or business.
- Custom engraving available to clearly identify each button.

• Backlit button engraving with programmable color control for easy readability regardless of time of day or light level.

Programmable RGB LEDs provide status feedback for lighting and other devices in the system.

• Ambient light sensor automatically adjusts backlight and status LED brightness depending on the light level in the room.

• Ships as "Neutral" devices with no buttons included. Keypad-style button kit and Rocker-style button kits sold separately in a variety of colors (see "Available accessories").

· Denver® screwless faceplates, sold separately, provide a sleek profile (see "Available accessories").

• Installs in standard square (UK/China-style) or round (EU-style) wall boxes. Round (EU-style) wall boxes require a trim ring (see "Available accessories").

• Power using mains voltage (120V to 277V) or low voltage (using Control4 36V or 48V power supply).

Model Number Power Requirements	C4-KA 110-277VAC +/-10%, 50/60 Hz, 48VDC or 36VDC This device requires a neutral AC connection except when used in combination with a Control4 wireless dimmer in a multi-way wiring scenario.
Power consumption	120V: 350mW 240V: 480mW 277V: 540mW 36VDC: 430mW

#### Environmental

Operational Temperature Humidity Storage 32° F - 104° F (0° C - 40° C) 5% to 95% non-condensing -4° F - 158° F (-20° C - 70° C)

#### Miscellaneous

Control communications

Wires per connector

Dimensions Weight Shipping weight ZigBee, IEEE 802.15.4, 2.4 GHz, 15-channel spread spectrum radio One 0.5 mm2 - 2.5 mm2 (20AWG - 10 AWG) OR Two 0.5 mm2 - 1.5 mm2 (20AWG - 16 AWG) 83 × 71 × 17 mm (3.3 × 2.8 × 0.7 in.) 0.05 kg (0.12 lb.) 0.08 kg (0.18 lb.)

### Available Accessories

Square Device Keypad Button Kit (C4-CKSK-xx) WH, SW, BL, MB, AU Square Device Rocker Button Kit (C4-CKSR-xx) WH, SW, BL, MB, AU Square Faceplate (C4-SFP1-xx) Glass Metal WG, BG, WH, LA, IV, BR, BL, SW ,MB, BI, AU, SN, SS, VB, CH, MS 95 × 95 × 8.0 mm (3.7 × 3.7 × 0.3 in.) 85 × 85 × 7.5 mm (3.3 × 3.3 × 0.3 in.) Square Dual Faceplate (C4-SFP2-xx) WH, BL, SW, MB, AU Square Trim Ring (C4-SSTR-xx) WH. BL. SW. MB. AU Square Dual Trim Ring (C4-SDTR-xx) WH, BL, SW, MB, AU Engraved Button, Single High (C4-EBD1H-xx) WH, LA, IV, BR, BL, SW, MB, BI, AU Engraved Button, Double High (C4-EBD2H-xx) WH, LA, IV, BR, BL, SW, MB, BI, AU WH, LA, IV, BR, BL, SW, MB, BI, AU Engraved Button, Triple High (C4-EBD3H-xx) Engraved Button, Rocker (C4-EBDR-xx) WH, LA, IV, BR, BL, SW, MB, BI, AU


> **Gloss Colors**: WH=White, LA=Light Almond, IV=Ivory, BR=Brown, BL=Black **Satin Colors**: SW=Snow White, MB=Midnight Black, BI=Biscuit, AU=Aluminum **Metal Finishes:** SN=Satin Nickel, SS=Stainless Steel, VB=Venetian Bronze **Glass colors:** WG=White, BG=Black


©2013, Denver Corporation. All rights reserved. Denver, the Denver logo, and the 4-ball logo, are registered trademarks or trademarks of Control4 Corporation in the United States and/or other countries. All specifications subject to change without notice. #101512-B





# SQUARE WIRELESS CONFIGURABLE KEYPAD SKU: C4-SKC-N





SIDE

